

NEW

**power contactors CX³
without handle**
from 16 A to 63 A

**auxiliaries
for contactors CX³**



4 125 05



4 125 35



4 124 29



4 124 31

Dimensions **see e-catalogue**
Technical characteristics **p. 86**

Conform to IEC/EN 61095
Space for power supply busbar on top (up to 25 A)

Power contactors with 24 V~ coil

Pack	Cat.Nos		Connection	Type of contact	Number of modules
1	4 125 03	2-pole - 250 V~ I max 16 A		N/C + N/O	1
1	4 125 05	25 A		2 N/O	1
1	4 125 10	4-pole - 400 V~ 25 A		4 N/O	2
1	4 125 09	25 A		2 N/C + 2 N/O	2

Power contactors with 230 V~ coil

Pack	Cat.Nos		Connection	Type of contact	Number of modules
4	4 125 21	2-pole - 250 V~ I max 16 A		N/C + N/O	1
10	4 125 23	25 A		2 N/O	1
1	4 125 27	63 A		2 N/O	2
1	4 125 24	25 A		2 N/C	1
5	4 125 35	4-pole - 400 V~ 25 A		4 N/O	2
1	4 125 41	63 A		4 N/O	3
1	4 125 36	25 A		4 N/C	2
1	4 125 33	25 A		2 N/C + 2 N/O	2

Signalling auxiliaries for contactors

Auxiliary changeover switch
Used to signal the position status of the contacts on the product to which it is connected

Pack	Cat.Nos		I max	Voltage	Contact	Number of modules
1	4 124 29	For 1 module contactors 16 A to 25 A Maximum 2 auxiliary devices per contactor Fitted on left-hand side of contactor	5 A	250 V~	N/C + N/O	0.5
1	4 124 30	For 2 module contactors 25 A Maximum 2 auxiliary devices per contactor Fitted on left-hand side of contactor	5 A	250 V~	N/C + N/O	0.5
1	4 124 31	For 40 and 63 A contactors Maximum 1 auxiliary device per contactor Fitted on left-hand side of contactor	5 A	250 V~	N/C + N/O	0.5



For detailed dimensions,
see e-catalogue