

# E4H-A 3200 PR121/P-LSIG

## In=3200A 3p W MP

E4H-A 3200 PR121/P-LSIG In=3200A 3p W MP



### General Information

Extended Product Type	E4H-A 3200 PR121/P-LSIG In=3200A 3p W MP
Product ID	1SDA057889R1
EAN	8015644601522
Catalog Description	E4H-A 3200 PR121/P-LSIG In=3200A 3p W MP
Long Description	SACE EMAX MOVING PART FOR CIRCUIT-BREAKER E4H-A 3200A UL THREE-POLE OVERCURRENT RELEASE PR121/P-LSIG R3200 FITTED WITH: 4 AUXILIARY CONTACT AND C.BREAKER IN POSITION OPEN-CLOSED

### Ordering

EAN	8015644601522
Minimum Order Quantity	1 piece
Customs Tariff Number	85362090

### Dimensions

Product Net Width	594 mm
Product Net Height	461 mm
Product Net Depth / Length	396.5 mm
Product Net Weight	85 kg

### Container Information

Package Level 1 EAN	8015644601522
---------------------	---------------

### Additional Information

Current Type	AC
Electrical Durability	Ue =< 508 V 5000 cycle Ue = 508 ... 635 V 5000 cycle 30 cycles per hour
Mechanical Durability	8000 cycle 30 cycles per hour
Number of Poles	3
Power Loss	at Rated Operating Conditions per Pole 422 W
Product Main Type	SACE Emax
Product Name	Air Circuit Breaker

Product Type	Air Circuit Breaker
Rated Current ( $I_n$ )	3200 A
Rated Voltage ( $U_r$ )	600 V
Rated Operational Current ( $I_e$ )	3200 A
Rated Service Short-Circuit Breaking Capacity ( $I_{cs}$ )	(240 V AC) 100 kA (480 V AC) 85 kA (600 V AC) 85 kA
Rated Uninterrupted Current ( $I_u$ )	3200 A
Release Type	EL
Standards	UL
Sub-type	E4
Terminal Connection Type	Withdrawable Circuit-Breakers
Version	W

### Certificates and Declarations (Document Number)

Data Sheet, Technical Information	1SDC200008D0202
Declaration of Conformity - CE	1SDL000165R0016
Instructions and Manuals	1SDH000532R0002

### Classifications

ETIM 4	EC000228 - Power circuit-breaker for trafo/generator/installation prot.
ETIM 5	EC000228 - Power circuit-breaker for trafo/generator/installation prot.
ETIM 6	EC000228 - Power circuit-breaker for trafo/generator/installation prot.

### Categories

Low Voltage Products and Systems → Circuit Breakers → Air Circuit Breakers → Emax

