

E6V-A 5000 PR123/P-LSIG In=5000A 3p W MP

E6V-A 5000 PR123/P-LSIG In=5000A 3p W MP



General Information

Extended Product Type	E6V-A 5000 PR123/P-LSIG In=5000A 3p W MP
Product ID	1SDA058133R1
EAN	8015644603960
Catalog Description	E6V-A 5000 PR123/P-LSIG In=5000A 3p W MP
Long Description	SACE EMAX MOVING PART FOR CIRCUIT-BREAKER E6V-A 5000A UL THREE-POLE OVERCURRENT RELEASE PR123/P-LSIG R5000 FITTED WITH: 4 AUXILIARY CONTACT AND C.BREAKER IN POSITION OPEN-CLOSED

Ordering

EAN	8015644603960
Minimum Order Quantity	1 piece
Customs Tariff Number	85362090

Dimensions

Product Net Width	810 mm
Product Net Height	461 mm
Product Net Depth / Length	396.5 mm
Product Net Weight	116 kg

Container Information

Package Level 1 EAN	8015644603960
---------------------	---------------

Additional Information

Current Type	AC
Electrical Durability	Ue =< 508 V 3000 cycle Ue = 508 ... 635 V 3000 cycle 30 cycles per hour
Mechanical Durability	8000 cycle 30 cycles per hour
Number of Poles	3
Power Loss	at Rated Operating Conditions per Pole 700 W
Product Main Type	SACE Emax
Product Name	Air Circuit Breaker

Product Type	CBMP
Rated Current (I_n)	5000 A
Rated Voltage (U_r)	600 V
Rated Operational Current (I_e)	5000 A
Rated Service Short-Circuit Breaking Capacity (I_{cs})	(240 V AC) 125 kA (480 V AC) 125 kA (600 V AC) 100 kA
Rated Uninterrupted Current (I_u)	5000 A
Release Type	EL
Standards	UL 1066
Sub-type	E6
Terminal Connection Type	Withdrawable Circuit-Breakers
Version	W

Certificates and Declarations (Document Number)

Data Sheet, Technical Information	1SDC200008D0202
Declaration of Conformity - CE	1SDL000165R0017
Instructions and Manuals	1SDH000532R0002

Classifications

ETIM 4	EC000228 - Power circuit-breaker for trafo/generator/installation prot.
ETIM 5	EC000228 - Power circuit-breaker for trafo/generator/installation prot.
ETIM 6	EC000228 - Power circuit-breaker for trafo/generator/installation prot.
WEEE Category	4. Large Equipment (Any External Dimension More Than 50 cm)

Categories

Low Voltage Products and Systems → Circuit Breakers → Air Circuit Breakers → Emax

