








Disconnect Switches










Technical Information Switching diagrams

Switching diagrams 41600–41800










Main/Emergency-Off Switches · Main Switches · ON-OFF Switches, 6 pole

41600	1L1	1L2	1L3	2L1	2L2	2L3
						
	1T1	1T2	1T3	2T1	2T2	2T3
SMD	41600					












Switching programme 41600
6 pole without auxiliary contacts

41611	1L1	1L2	1L3	2L1	2L2	2L3	21	13
								
	1T1	1T2	1T3	2T1	2T2	2T3	22	14
SMD	41600						MB	












Switching programme 41611
6 pole with 2 auxiliary contacts
1 n/o late make/early break + 1 n/c

41620	1L1	1L2	1L3	2L1	2L2	2L3	33	43
								
	1T1	1T2	1T3	2T1	2T2	2T3	34	44
SMD	41600						MD	












Switching programme 41620
6 pole with 2 auxiliary contacts
2 n/o late make/early break

41622	24	32	1L1	1L2	1L3	2L1	2L2	2L3	21	13
										
	23	31	1T1	1T2	1T3	2T1	2T2	2T3	22	14
SMD	MC		41600						MB	

Switching programme 41622
6 pole with 4 auxiliary contacts
2 n/o late make/early break + 2 n/c










41631	44	34	1L1	1L2	1L3	2L1	2L2	2L3	21	13
										
	43	33	1T1	1T2	1T3	2T1	2T2	2T3	22	14
SMD	MD		41600						MB	

Switching programme 41631
6 pole with 4 auxiliary contacts
3 n/o late make/early break + 1 n/c

41640	64	54	1L1	1L2	1L3	2L1	2L2	2L3	33	43
										
	63	53	1T1	1T2	1T3	2T1	2T2	2T3	34	44
SMD	ME		41600						MD	

Switching programme 41640
6 pole with 4 auxiliary contacts
4 n/o late make/early break

ON-OFF Switches, 8 pole

41800	N	1L1	1L2	1L3	2L1	2L2	2L3	N
								
	N	1T1	1T2	1T3	2T1	2T2	2T3	N
SMD	MA	41600						MA

Switching programme 41800
8 pole without auxiliary contacts
2 neutral contacts early make/late break