

E1B/EMS12504p1000VDCWMPnew



E1B/E MS 1250 4p 1000V DC W MP new



General Information

Extended Product Type	E1B/EMS12504p1000VDCWMPnew
Product ID	1SDA059048R1
EAN	8015644614072
Catalog Description	E1B/E MS 1250 4p 1000V DC W MP new
Long Description	SACE EMAX MOVING PART FOR C.BREAKER SWITCH-DISCONNECTOR E1B/E MS 1250A 1000V DC FOUR-POLE NEW

Ordering

EAN	8015644614072
Minimum Order Quantity	1 piece
Customs Tariff Number	85362090

Dimensions

Product Net Width	414 mm
Product Net Height	461 mm
Product Net Depth / Length	396.5 mm
Product Net Weight	54 kg

Container Information

Package Level 1 Units	1 piece
Package Level 1 Width	515 mm
Package Level 1 Height	600 mm
Package Level 1 Depth / Length	615 mm
Package Level 1 Gross Weight	67 kg
Package Level 1 EAN	8015644609139

Additional Information

Current Type	DC
Electrical Durability	10000 cycle 30 cycles per hour
Mechanical Durability	25000 cycle 60 cycles per hour

Number of Poles	4
Power Loss	230 W
Product Main Type	SACE Emax
Product Name	Switch Disconnecter
Product Type	Air Circuit Breaker
Rated Current (I_n)	1250 A
Rated Voltage (U_r)	1000 V
Rated Impulse Withstand Voltage (U_{imp})	12 kV
Rated Insulation Voltage (U_i)	1000 V
Rated Operational Current (I_e)	1250 A
Rated Operational Voltage	1000 V DC
Rated Short-time Withstand Current (I_{cw})	for 1 s 20 kA
Rated Uninterrupted Current (I_u)	1250 A
Standards	IEC
Sub-type	E1
Terminal Connection Type	Withdrawable Circuit-Breakers
Version	W

Certificates and Declarations (Document Number)

Data Sheet, Technical Information	1SDC200012D0202
Declaration of Conformity - CE	1SDL000165R0013
Instructions and Manuals	1SDH000635R0002

Classifications

ETIM 4	EC000228 - Power circuit-breaker for trafo/generator/installation prot.
ETIM 5	EC000228 - Power circuit-breaker for trafo/generator/installation prot.
ETIM 6	EC000216 - Switch disconnecter
ETIM 7	EC000216 - Switch disconnecter
Object Classification Code	Q
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)

Categories

Low Voltage Products and Systems → Circuit Breakers → Air Circuit Breakers → Emax

