

E1N-A 1200 PR121/P-LSI In=1200A 3p F HR

E1N-A 1200 PR121/P-LSI In=1200A 3p F HR



General Information

Extended Product Type	E1N-A 1200 PR121/P-LSI In=1200A 3p F HR
Product ID	1SDA060951R1
EAN	8015644634742
Catalog Description	E1N-A 1200 PR121/P-LSI In=1200A 3p F HR
Long Description	SACE EMAX CIRCUIT-BREAKER E1N-A 1200A UL THREE-POLE FIXED WITH TERMINALS REAR HORIZONTAL OVERCURRENT RELEASE PR121/P-LSI R1200 FITTED WITH: 4 AUXILIARY CONTACT AND C.BREAKER IN POSITION OPEN-CLOSED

Ordering

EAN	8015644634742
Minimum Order Quantity	1 piece
Customs Tariff Number	85362090

Dimensions

Product Net Width	296 mm
Product Net Height	418 mm
Product Net Depth / Length	302 mm
Product Net Weight	40 kg

Container Information

Package Level 1 EAN	8015644609139
---------------------	---------------

Additional Information

Current Type	AC
Electrical Durability	Ue =< 508 V 10000 cycle Ue = 508 ... 635 V 10000 cycle 30 cycles per hour
Mechanical Durability	20000 cycle 30 cycles per hour
Number of Poles	3
Power Loss	at Rated Operating Conditions per Pole 138 W
Product Main Type	SACE Emax
Product Name	Air Circuit Breaker

Product Type	CB
Rated Current (I_n)	1200 A
Rated Voltage (U_r)	600 V
Rated Operational Current (I_θ)	1200 A
Rated Ultimate Short-Circuit Breaking Capacity (I_{cu})	(240 V AC) 50 kA (480 V AC) 50 kA (600 V AC) 50 kA
Rated Uninterrupted Current (I_u)	1200 A
Release Type	EL
Standards	UL 1066
Sub-type	E1
Terminal Connection Type	Fixed Circuit-Breakers Rear flat Horizontal
Version	F

Certificates and Declarations (Document Number)

Data Sheet, Technical Information	1SDC200008D0202
Declaration of Conformity - CE	1SDL000165R0013
Instructions and Manuals	1SDH000532R0002

Classifications

ETIM 4	EC000228 - Power circuit-breaker for trafo/generator/installation prot.
ETIM 5	EC000228 - Power circuit-breaker for trafo/generator/installation prot.
ETIM 6	EC000228 - Power circuit-breaker for trafo/generator/installation prot.
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)

Categories

Low Voltage Products and Systems → Circuit Breakers → Air Circuit Breakers → Emax

