



OUTPUT INTERFACE WITH PLUG-IN RELAY,
1 CHANGEOVER CONTACT SCREW TERMINAL 24 V DC
ENCLOSURE WIDTH 6.2 MM

General technical details:

type of voltage		DC
Control supply voltage		
<ul style="list-style-type: none"> • for DC / rated value • minimum • maximum 	V	24
	V	24
Switching behaviour		monostable
Number of NC contacts / for auxiliary contacts		0
Number of NO contacts / for auxiliary contacts		0
Number of changeover contacts / for auxiliary contacts		1
Operating current / of the auxiliary contacts		
<ul style="list-style-type: none"> • at DC-13 • at 24 V • at 110 V • at 230 V • at AC-15 • at 230 V 	A	1
	A	0.2
	A	0.1
	A	3
Item designation / according to DIN 40719 extendable after IEC 204-2 / according to IEC 750		K
Item designation / according to DIN EN 61346-2		K

Mechanical design:

Design of the electrical connection		screw-type terminals
Design of the electrical connection / jumper socket		Yes
Design of the relay operating mechanism		poled
Design of the switching function		changeover switch
• guided		No
Product component / jumper socket		Yes
Width	mm	6.2
Height	mm	89.5
Depth	mm	92

Ambient conditions:

Protection class IP		IP20
Ambient temperature		
• during operating	°C	-25 ... +55

Certificates/approvals:

General Product Approval



CCC



GOST



UL

Test Certificates

[Special Test Certificate](#)

other

[Declaration of Conformity](#)

Further information:

Information- and Downloadcenter (Catalogs, Brochures,...)

<http://www.siemens.com/industrial-controls/catalogs>

Industry Mall (Online ordering system)

<http://www.siemens.com/industrial-controls/mall>

CAX-Online-Generator

<http://www.siemens.com/cax>

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

<http://support.automation.siemens.com/WW/view/en/3TX7014-1BM00/all>

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)

http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=3TX7014-1BM00

last change:

Jan 28, 2013