

# E6V-A 5000 PR121/P-LSI In=5000A 3p W MP

E6V-A 5000 PR121/P-LSI In=5000A 3p W MP



## General Information

Extended Product Type	E6V-A 5000 PR121/P-LSI In=5000A 3p W MP
Product ID	1SDA058109R1
EAN	8015644603724
Catalog Description	E6V-A 5000 PR121/P-LSI In=5000A 3p W MP
Long Description	SACE EMAX MOVING PART FOR CIRCUIT-BREAKER E6V-A 5000A UL THREE-POLE OVERCURRENT RELEASE PR121/P-LSI R5000 FITTED WITH: 4 AUXILIARY CONTACT AND C.BREAKER IN POSITION OPEN-CLOSED

## Ordering

EAN	8015644603724
Minimum Order Quantity	1 piece
Customs Tariff Number	85362090

## Dimensions

Product Net Width	810 mm
Product Net Height	461 mm
Product Net Depth / Length	396.5 mm
Product Net Weight	116 kg

## Container Information

Package Level 1 EAN	8015644603724
---------------------	---------------

## Additional Information

Current Type	AC
Electrical Durability	Ue =< 508 V 3000 cycle Ue = 508 ... 635 V 3000 cycle 30 cycles per hour
Mechanical Durability	8000 cycle 30 cycles per hour
Number of Poles	3
Power Loss	at Rated Operating Conditions per Pole 700 W
Product Main Type	SACE Emax
Product Name	Air Circuit Breaker

Product Type	CBMP
Rated Current ( $I_n$ )	5000 A
Rated Voltage ( $U_r$ )	600 V
Rated Operational Current ( $I_e$ )	5000 A
Rated Service Short-Circuit Breaking Capacity ( $I_{cs}$ )	(240 V AC) 125 kA (480 V AC) 125 kA (600 V AC) 100 kA
Rated Uninterrupted Current ( $I_u$ )	5000 A
Release Type	EL
Standards	UL 1066
Sub-type	E6
Terminal Connection Type	Withdrawable Circuit-Breakers
Version	W

### Certificates and Declarations (Document Number)

Data Sheet, Technical Information	1SDC200008D0202
Declaration of Conformity - CE	1SDL000165R0017
Instructions and Manuals	1SDH000532R0002

### Classifications

ETIM 4	EC000228 - Power circuit-breaker for trafo/generator/installation prot.
ETIM 5	EC000228 - Power circuit-breaker for trafo/generator/installation prot.
ETIM 6	EC000228 - Power circuit-breaker for trafo/generator/installation prot.
WEEE Category	4. Large Equipment (Any External Dimension More Than 50 cm)

### Categories

Low Voltage Products and Systems → Circuit Breakers → Air Circuit Breakers → Emax

