

- detects phase failure, phase sequence and phase asymmetry
- detects phase failure with regenerated voltage present
- SPCO or DPCO output max. 6A
- 🔷 fixed asymmetry alarm TCP / PCP >10% TCP-L / PCP-L >30%
- no neutral connection required
- 🔷 adjustable reaction timer 0.1 10s
- LED indicators for power supply, relay and reaction timer
- 22.5 or 45mm DIN rail mount housing or 11pin plug in housing




supply voltage variation	nominal voltage +10% / -15%			
frequency range	48 - 63 Hz			
duty cycle	100%			
reaction timer	0,1 - 10s			
reset time	< 100ms			
output relay specification	max. 6A 230V~			
Ue/le AC-15	120V/4A 240V/3A			
Ue/le DC-13	24V/2A			
expected life time	DPCO SPCO			
mechanical	2×10^6 resp. 1×10^7 operations			
electrical	1 x 10 ⁵ resp. 1 x 10 ⁵ operations			
screws	pozidrive 1			
screw tightening torque	0,60,8Nm			
operating conditions	-20 to +60 °C non condensing			
	* EN 60947-5-1 VDE 0435			



Function

Control relay active





Control relay to monitor 3-wire, 3-phase systems for the failure of one or more phase, a phase asymmetry shift exceeding 10% and the correct phase rotation (L1, L2, L3)
The TCP detects that the phase sequence is correct and that no phase

has failed, in which case the output relay R energises. At a loss of one phase (> 25% under nominal voltage) or at a detection of an asymmetry shift (> 10%), the reaction time t starts. At the end of time t the output relay R de-energises. Time t is adjustable between 0.1s and 10s and is used to time out short transients which would

otherwise cause nuisance tripping.
The relay energises again when phase L1, L2 and L3 return to within the permitted range.

The control relay will detect a phase failure even with a regenerated voltage present on the failed phase (no detection on request).





ordering information

part no	supply	output	sup. galv. iso*	: ''.' :	housing types	
TCP 3x400Vac	3x 400V~ 2,5VA	DPCO	yes	yes	С	
TCP 3x230Vac	3x 230V~ 2,5VA	DPCO	yes	yes	С	
TCP-S 3x400Vac	3x 400V~ 2,5VA	SPCO	yes	yes	В	
TCP-S 3x230Vac	3x 230V~ 2,5VA	SPCO	yes	yes	В	
PCP 3x400Vac	3x 400V~ 2,5VA	DPCO	yes	no	G	
PCP 3x230Vac	3x 230V~ 2,5VA	DPCO	yes	no	G	
TCP-L 3x400Vac	3x 400V~ 2,5VA	DPCO	yes	no	С	
TCP-L 3x230Vac	3x 230V~ 2,5VA	DPCO	yes	no	С	
PCP-L 3x400Vac	3x 400V~ 2,5VA	DPCO	yes	no	G	
PCP-L 3x230Vac	3x 230V~ 2,5VA	DPCO	yes	no	G	
* TI	the state of the state of					

^{*} The measurement input is galvanically isolated from the power supply























